



ARF-WL8-IN

Wireless input module

The wireless input module is used for monitoring one input circuit and sending information to the control panel



FEATURES:

- Programmable input for fire and security detectors, emergency button or specialized detectors
- Bi-directional wireless communication
- Fully intelligent
- 10-year battery life
- Self-optimizing wireless frequency and amplitude algorithms
- Operating temperature range: -10 °C to +55 °C



The product complies with the requirements of the EN54-18:2005, EN54-25:2008 standards

